

ACMEDA – Roller Blinds

Motor: EL Motor – Wired AC Motor

Remote: Automate | 15CH ARC Remote

REMOTE – **Insert Battery**

MOTOR – **Connect Power**

FACTORY RESET

Select Channel	
REMOTE – PRESS [P2]	
REMOTE – PRESS [STOP]	
REMOTE – PRESS [P2]	<i>beep&jolt</i>

PAIRING *within 10secs*

Select Channel	
MOTOR – Connect Power	<i>beep&jolt</i>
REMOTE – PRESS [P2]	
REMOTE – PRESS [P2]	
REMOTE – PRESS [DOWN]	<i>beep&jolt</i>

REVERSE ROLL DIRECTION *if required*

REMOTE – HOLD [STOP]	<i>beep&jolt</i>
----------------------	----------------------

SET LIMITS

REMOTE – PRESS [P2]	
REMOTE – PRESS [UP]	
REMOTE – PRESS [P2]	<i>beep&jolt</i>
UP Limit FIRST	
REMOTE – PRESS [P2]	<i>step mode</i>
REMOTE – HOLD [STOP]	<i>beep&jolt</i>
DOWN Limit SECOND	
REMOTE – PRESS [P2]	<i>step mode</i>
REMOTE – HOLD [STOP]	<i>beep&jolt</i>

DELETE LIMITS

Select Channel	
REMOTE – PRESS [P2]	
REMOTE – PRESS [DOWN]	
REMOTE – PRESS [P2]	<i>beep&jolt</i>